

## Installing the MMM Ricoh IM C3000 Printer – Windows 10 Instructions

### Download the printer driver:

- Download the **PCL 6** driver from the web:  
[https://support.ricoh.com/bb/html/dr\\_ut\\_e/rc3/model/imc3000/imc3000.htm](https://support.ricoh.com/bb/html/dr_ut_e/rc3/model/imc3000/imc3000.htm)
- Select **PCL 6 Driver** and **Download**. After the download completes, browse out to C:\Downloads and open **z94761L18.exe** Double-click on the file and **Unzip** to extract. Please make note of the folder location where it's unzipping to: For example: C:\temp\z94761L18.exe

### To add the printer:

- Next to the **Start** menu, search for, and select **Control Panel**
- Click **Devices and Printers**, then click **Add a printer** (along the top menu bar)
- Click on **the printer that I want isn't listed**
- Click **Add a printer using TCP/IP address or hostname**
- Click **Next**
- For Device Type, select **TCP/IP Device**, for Hostname or IP address, type: 129.105.102.61 and **un-check** "Query the printer and automatically select the driver to use". Click **Next**
- Click the **Have Disk...** button.
- Click **Browse...** and navigate to where you extracted the printer driver files, for example:  
C:\temp\z94761L18\disk1
- Double-click folders in succession (downloaded folder location → z94761L18 → disk1 until you see **oemsetup.inf** and double-click this file – then click **OK**
- Select the **Ricoh IM C3000 PCL 6** and click **Next**
- *Recommended:* Modify the name to better identify this printer, *e.g.:* **Segal Ricoh IM C3000 PCL 6** (whatever best describes the printer to you). Click **Next**
- Select the **Do not share this printer** radio button and click **Next**
- Click **Finish**.

You should now be able to print to this printer.